HD60 USB 2.0 Pro Capture NS110

User Manual



Contents

1. Hardware Installation Error! Bookmark not defined.					
	1.1	Package Contents3			
	1.2	System Requirements3			
	1.3	Hardware Configuration4			
	1.4	Hardware Installation Diagram5			
2. Soft	tware	e Installation6			
	2.1	Screen Recorder 4 Installation6			
	2.2	PowerDirector 15 Installation9			
3. FAC)				
	3.1	How to check if the driver has been installed successfully or not ?			

1. Hardware Installation

1.1 Package Contents

Unpack your package and make sure that all items are intact. The following items should be included in your package:

- HD60 USB 2.0 Pro Capture
- Quick Start Guide Download Helper
- Software Serial Number
- HDMI Cable
- Micro USB Cable



1.2 System Requirements

- Intel® Core[™] i5-3330 or above (recommend i7)
 NVIDIA® GeForce® GTX 650 / AMD Radeon[™] R7 250X or above
- 4GB RAM
- One available USB2.0 port
- Independent Graphics card
- Sound Card (AC97 compatible sound card)
- 1GB Free HD Space
- CD-ROM Drive (For software installation)
- Microsoft Windows 8 / 8.1 and Windows 10 operation system
- Mac OS X 10.10 or later

1.3 Hardware Configuration

• LED

Status	Color	LED Action	
Standby ready	Green	Light up constantly	
(UVC Mode/SD Card Mode)			
No input source detected	Red	Light up constantly	
Card Reader Mode ready	Blue	Light up constantly	
UVC Mode is recording by AP	Green	Blink	
Recording into SD Card	Green	Blink	
Error	Red	Blink	

Button and Switch





Item	Function Description
Top Button	Record in SD Card Mode / Go to Card Reader when pressing 3 sec in PC Mode
Side Button	Snapshot in SD Card Mode.
Mode Switch	Switch SD Card Mode / PC Mode
Micro SD Slot	Save snapshot pic and record video .

1.4 Hardware Installation Diagram

- Standard video recording application on PC - (Needs an extra HDMI Splitter.)



- SD Card video recording application - (Needs an extra HDMI Splitter.)



2. Software Installation

2.1 Screen Recorder 4 Installation

Step 1 : Enter Narvitech.com

Go to the upper right corner click [Support]>[Download]. On the "Download" page, go

to [NS110]>[Software]>[CyberLink Screen Recorder 4], then click download.

About Narvitech	Product	Support	Languages
	About Narvitech	About Narvitech Product	About Narvitech Product Support

Step 2 : After downloading, unzip the uncompressed file folder. Find and click on

[Setup.exe].



Step 3 : Select Language and Location.



Step 4 : Click Accept







Step 6 : Restart after installation and enter serial number.



Step 7 : Enter serial number and start to use [Screen Recorder 4].



2.2 PowerDirector 15 Installation

Step 1 : Enter Narvitech.com. Go to upper right corner [Support]>[Download]. Go to

[NS110]>[Software]>[CyberLink PowerDirector 15] on "Download" page, then

click download.



Step 2 : After downloading, unzip the compressed file folder. Find and click on [Setup.exe].



Step 3 : Select Language and Location.



Step 4 : Click Accept



Step 5 : Installation in progress.



Step 6 : Launch the program after installation is complete.



Step 7 : Click on any mode and enter serial number.



Step 8 : Enter serial number and start to use [PowerDirector 15].



3. FAQ

3.1 How to check if the driver has been installed successfully or

not?

Check the status of device in Device Manager.

Device name: NarviCaptre U2 HD60 Pro

Sound device: NarviCaptre U2 HD60 Pro °

Please refer to figure 1.

🛃 Device Manager			1000	×
File	Act	ion View Help		
A				
× 🗄	P15	5F-AX64E		
~	4	Audio inputs and outputs		
		🖳 Microphone (2- Realtek High Definition Audio)		
		📮 Microphone (NarviCapture U2 HD60 Pro)		
		🏹 Speakers (2- Realtek High Definition Audio)		
>	5	Batteries		
>	8	Bluetooth		
~	Q	Cameras		
		🧶 Chicony USB 2.0 Camera		
		NarviCapture U2 HD60 Pro		
>	-	Computer		
>	-	Disk drives		
>	-	Display adapters		
>	-	DVD/CD-ROM drives		
>	Pro	Human Interface Devices		
>	-	IDE ATA/ATAPI controllers		
>		Keyboards		
>		Memory technology devices		
>	U	Mice and other pointing devices		
>		Monitors		
>	F	Network adapters		
>	-	Portable Devices		
>	-	Print queues		
>	H	Processors		
,	-	Software components		
2		Software devices		
~	4	Sound, video and game controllers		
		NaniCaptura LI2 HD60 Pro		
		Realtek High Definition Audio		
,	G	Storage controllers		
2	Ē	System devices		
ے د		Universal Serial Bus controllers		
	т			